

Sol. No	Solenoid description	Solenoid Type	Wire Code	Wire Color	Connector	Driver Transistor	Solenoid Coil Type
1	Not Used	Momentary	31	Yel-Red	J6-1, J8-5	Q11	-
2	Middle Thumper Bumper	Momentary	32	Yel-Blu	J6-2, J8-4	Q12	A-26-1200
3	Left Thumper Bumper	Momentary	34	Yel-Gm	J6-3	Q13	A-26-1200
4	Right Thumper Bumper	Momentary	35	Yel-Whi	J6-4	Q14	A-26-1200
5	Left Slingshot	Momentary	27	Blu-Orn	J8-7, J7-1	Q16	A-26-1200
6	Right Slingshot	Momentary	25	Blu-Whi	J8-6	Q15	A-26-1200
7	Ball Save	Momentary	36	Yel-Brn	J6-5	Q17	A-26-1200
8	Not Used	Momentary	51	Whi-Red	J9-1	Q18	-
9	Saucer	Momentary	52	Whi-Blu	J9-2	Q19	A-27-1300
10	Open Atom Smasher	Momentary	53	Whi-Yel	J9-3	Q20	A-26-1200
11	Close Atom Smasher	Momentary	54	Whi-Gm	J9-4	Q21	5-31-1800
12	Kicker	Momentary	56	Whi-Brn	J9-6	Q22	A-27-1300
13	(German games)	Momentary	57	Whi-Orn	J9-7	Q38	<del>A-26-1200</del> A-26-1200
14	Outhole	Momentary	58	Whi-Blk	J9-8	Q39	<del>A-26-1200</del> A-26-1200
15	Knocker	Momentary	59	Whi-Gry	J7-2, J8-2, J9-11	Q40	<del>A-26-1200</del> A-26-1200
16	Not Used	Continuous	511	Whi-Vio	J9-9	Q9	-
17	Neon Display	Momentary	311	Yel-Vio	J6-7, J7-4	Q10	Solid State Relay Bd.
18	Back Box Lights	Continuous	24	Blu-Gm	J7-3, J8-1, J9-10	Q8	Solid State Relay Bd.
19	Flippers	Continuous	--	--	--	Q7	48V Relay
	Right Flipper Coil						A-24-570/34-8600
	Upper Right Flipper Coil						A-24-570/34-8600
	Left Flipper Coil						A-24-570/34-8600